

Produktblad Yamaha Ri8-D

Digital Stagebox 19 "1He, 8 ingångar.

General specifications

Sampling frequency rate

External 44.1kHz: +4.1667%, +0.1%, -0.1%, -4.0%
(±200ppm) / 48kHz: +4.1667%, +0.1%, -0.1%, -4.0%
(±200ppm) / 88.2kHz: +4.1667%, +0.1%, -0.1%, -4.0%
(±200ppm) / 96kHz: +4.1667%, +0.1%, -0.1%, -4.0%
(±200ppm)

Signal delay Less than 3ms INPUT to OUTPUT, connect with CL5 using Dante, Dante Receive Latency set to 0.25ms (one way), Fs=48kHz

Total harmonic distortion Less than 0.05% 20Hz-20kHz@+4dBu into 600Ω, Fs=44.1kHz, 48kHz / Less than 0.05% 20Hz-40kHz@+4dBu into 600Ω, Fs=88.2kHz, 96kHz INPUT to OUTPUT, Input Gain = Min.

Frequency response +0.5, -1.5dB 20Hz-20kHz, refer to +4dBu output @1kHz, INPUT to OUTPUT, Fs=44.1kHz, 48kHz / +0.5, -1.5dB 20Hz-40kHz, refer to +4dBu output @1kHz, INPUT to OUTPUT, Fs=88.2kHz, 96kHz

Dynamic range 108dB typ., INPUT to OUTPUT, Input Gain = MinCrosstalk -100dB, adjacent INPUT/OUTPUT channels, Input Gain = Min.

Power requirements US/Canada: 120V 60Hz, Japan: 100V 50/60Hz, China: 110-240V 50/60Hz, Korea: 220V 60Hz, Other: 110-240V 50/60Hz

Power consumption 35W

Dimensions

W 480mm (18 7/8in)
H 44mm (1 3/4in)
D 362mm (14 1/4in)

Net weight 4.5kg (9.9lbs)

Others Temperature Range: Operating temperature range: 0 - 40°C, Storage temperature range: -20 - 60°C;

YARI8-D Yamaha Ri8-D 26810 kr inklusive moms

Lagerstatus: Ungefär 5 dagar

