

Produktblad ROLLS RM316

ROLLS RM316 Användarvänlig zonmixer med tre zoner

RM316 Three Zone Mixer kombinerar tre

mikrofoner eller XLR-linjenivåsignaler med tre RCA-linjenivåingångar. Varje ingång skickas enkelt ut till valfri kombination av tre zonutgångar via knappar på frontpanelen. Utgångarna är alla balanserade Phoenix-kontakter och har möjlighet att fjärrstyras via extern potentiometer. Mikrofoningångarna har valbar duckning och paging för varje enskild zon. RM316 är lätt för alla att använda och är precis tillräckligt komplex för att fylla även de mest krävande installationskraven med tre zoner. RM316 är den perfekta lösningen för restauranger, kontor, nattklubbar etc. Three Mic Inputs with independent switchable phantom power Three RCA source inputs and one front panel 3.5mm stereo input Three Balanced Phoenix Connector Zone Outputs Remote Volume for each output



 Specifications: Input Impedance: 10K Ohms balanced Line Output Impedance: 50 Ohms balanced Max Input Level: Mic: -30 dB Source: +22 dB Phantom Power: +15 Volts DC Max Gain: 60 dB mic 30 dB line S/N Ratio: större än 75 dB THD: < .3% IMD (SMPTE): < .3% CMRR: 60 dB Frequency Response: 20Hz to 20kHz +/- 0 dB

XL9122116 ROLLS RM316 5450 kr inklusive moms

Lagerstatus: Ungefär 5 dagar