## Produktblad sE Electronics sE8 (Pair)

sE Electronics sE8 (Pair) Probably the lowest self noice small-capsuled microphones on the planet. Matched Pair

Fit for any challenges in the studio or on stage, the

sE8 is a brand new high-performance handcrafted smalldiaphragm condenser, fresh from the labs at sE.Its new hand-made capsule implements a sophisticated backplate design that provides a perfectly balanced sound, so it's never harsh or aggressive - perfect for sources like high-hats and drum overheads. It's also one of the quietest small-capsule mics on the planet - and with the highest dynamic range and SPL handling in its class, along with attenuation pads and low-cut filters for superb flexibility, the sE8 is ready for any sounds you're making, whether in the studio environment or demanding on-stage applications. As with all SE factory-matched pairs, every mic ending up in a sE8 Stereo Pair configuration is hand-selected from hundreds of individual microphones. This ensures identical performance and the highest possible mic-to-mic consistency, so you can rest assured that your stereo image will be as clear & accurate as possible.HANDCRAFTED TRUE CONDENSER CAPSULE Gold-sputtered diaphragms ensure maximum reliability every capsule is handcrafted and individually tuned in our very own factory ultraprecision electrode design optimized for superb linearity and natural sonics ultra-thin 3 micron gold-sputtered diaphragm for superior transients newly-developed backplate design provides smooth, natural sound & truly consistent off-axis response sophisticated acoustic design with precision components avoids coloration in demanding applications MIC IN ITS CLASS sophisticated electronic design provides extremely low noise without the use of integrated circuits transformer less design for excellent transparency and clarity proven Class-A circuitry ensures a high dynamic range without distortion and brilliant transient response PRE-ATTENUATION PADSThe -10 dB and -20 dB pad switches provide extended dynamic range, enabling a wide range of applications and close-mic techniques for brass instruments, snare drums, and more.TWO SWITCHABLE LOW-CUT FILTERSSelectable at either 80Hz or 160Hz, these two filters help eliminate lowfrequency rumble or footfall noise, as well as help compensate for excessive bass (proximity effect) with close-mic techniques.ALL-METAL HOUSING WITH GOLD-PLATED XLR CONNECTOR, PREMIUM FINISH & ACCESSORIESUnlike the cheaply constructed bodies of some small-capsule microphones, the sE8's all-metal chassis provides efficient rejection of any electrical interference and noise - and the high-quality finish and gold-plated XLR connector ensures a great look and a loss-free, reliable signal connection for years to come.



The sE8 also comes standard with a newly-designed mic clip that will securely attach it to any mic stand. The sE8 Matched Pair comes complete with a precision stereo mounting bar, two protective wind screens, two mic clips, and a robust high-quality metal flight case.

**Specifications** Capsule Type: Hand-Crafted Small-Diaphragm True Condenser Polar Pattern: Cardioid Frequency range: 20 Hz - 20 kHz Sensitivity: 25 mV/Pa (-32 dBV) Max SPL: 139 / 149 / 159 dBSPL (0/10/20 dB pad) (0.5% THD @ 1kHz) Equivalent noise level: 13 dB(A) I) Dynamic range: 126 / 136 / 146 dB (0/10/20 dB Attentuation pad) Signal to Noise Ratio: 81 dB Low-cut filter: 80 / 160 Hz, 6 dB/Oct, switchable Attenuation Pad: 10 / 20dB, switchable Powering: 48 Volts according to IEC 61938 Electrical Impedance: 110 Ohms Recommended load impedance: större än 1k Ohms Current consumption: 2.7 mA Connectivity: 3-pin male XLR connector Dimensions: Diameter: 23mm (0.91 in), Length 120mm (4.72 in) Weight: 141 g 

XL1312882 sE Electronics sE8 (Pair) 4295 kr inklusive moms

Lagerstatus: Ungefär 5 dagar

2 av 2